

# Change Over M X H

Part no. 5100066-01A

G001129

System: Salwico Cargo, Salwico Cruise, Salwico LNG, Salwico Offshore, Salwico Ro/Pax, Salwico Workboat, Salwico Yacht, Salwico Navy, OEM Extinguish, CGD50/500, CGS50/500

## General Description

The Change Over M X can switch automatically between two power sources, mains and emergency, with preference towards mains power if both sources are operational.

The Change Over M X is used to connect to the PSU module in a system, and is also provided with one extra power supply outlet (which can be used for example to a printer). This is a separate module without any contact with the backbone bus.

For details on assembling a system and definitions of common system terms, refer to the Installation Manual.

## Data

Operating voltage range	85-264 VAC
Monitoring power	15-30 VDC
Max. output current	6 A (3A + 3A)
Cable terminals	2.5 mm <sup>2</sup>
Operating temperature range	-5°C to +55°C
Weight (with housing)	160g
Spare part no. (without housing)	5100065-02A
Certified according to	




2531/yy  
yy = year of  
production



2531-CPR-232.1686  
DOP no. 6301900

## Connections




G001199

CHANGE OVER M X		NUMBER	
POWER MONITORING EMCY	19-30 VDC	13	14
POWER MONITORING MAINS	19-30 VDC	12	11
85-264 VAC Max.3A	OUT 2	L	N
85-264 VAC Max.3A	OUT 1	L	N
EMERGENCY 85-264 VAC Max.6A	EMCY	L	N
MAINS 85-264 VAC Max.6A	MAINS	L	N

G002241

## Module Dimensions (mm)



G001137

## Mounting

Mount the module on a horizontal 35 mm DIN rail.